

# Meraki Wall Plug

## Specifications



Use the Meraki Wall Plug to cover large indoor areas with unparalleled speed. Simply plug the units into existing wall outlets to expand your network. Securely mount the Wall Plug onto the wall outlet with our innovative brackets. Also, as with all Meraki devices, the Wall Plug includes access to Meraki's unique Hosted Services.

### ➤ Installs Quickly

Plug the Meraki wireless repeater directly into most standard power outlets. There's no need to waste time hiding wires or mounting the unit to a wall. A typical installation takes 1-2 minutes and requires nothing more than a screwdriver.

### ➤ Compact

At about the size of two decks of cards, the Wall Plug is small enough to fit discretely in hallways or behind furniture.

### ➤ Typical Coverage Radius

- Indoor: 100 - 150 ft (30 - 50 m)

### ➤ Radio

- 60mW (18 dBm) peak transmission power
- 802.11 b/g (1-54 Mbps)
- Enhanced receive sensitivity
- Internal 2 dBi omni-directional antenna
- Internal diversity antenna

### ➤ Power

- 110 - 240 V 50/60 Hz AC input
- Power consumption: 7.5 W max; 3.5 W typical
- Available with US or EU plug type

### ➤ Secure Mounting

The Wall Plug features innovative secure mounting brackets that allow you to screw the device directly into the wall or outlet. The brackets deter theft and prevent accidental unplugging.

### ➤ Reliable

A hardware watchdog protects you from unpredictable events like power outages, making your network more reliable.

### ➤ Physical and Environment

- 4.1" x 2.5" x 2.5" (105 mm x 65 mm x 50 mm)
- Weight: 0.5 lb (0.25 kg)
- Operating temperature: 32° F – 104° F (0° C – 40° C)

### ➤ Interfaces / Ports

- Signal strength, power, and Ethernet LEDs
- One 10/100 Mbps auto-crossover Ethernet port: automatically detects PC or gateway operation

### ➤ Warranty

- 1 year hardware warranty included

### ➤ Regulatory

- UL Listed (USA)
- FCC (USA)
- CE (EU)
- IC (Canada)